



4-SOURCE 4-ZONE STEREO AUDIO POWER AMPLIFIER



With a diverse range of inputs, including digital (optical or coaxial) and dynamic microphone inputs, and the ability to adjust each zone's volume independently, the 4x4 amp is a quick and easy way of adding audio in up to four rooms. It also features a Loop-out for expanding to another unit, increasing the number of zones further!

Features

- Four-in and five-out
 - IN: 1x Digital (Optical / Coaxial selectable), 1x RCA Stereo, 1x 3.5mm Stereo, 1x Dynamic Microphone input
 - OUT: 4 Speaker output + 1 Headphone output
- Built-In audio digital to analogue converter (DAC)
 - Audio DAC Lock indicator
- Independent microphone level control
- Individual speaker volume control
- Provides line loop-out for expanding to more zones

- Large detachable terminal block (supplied) for quick and easy installation
 - Screw terminals handle wire sizes from 24 to 12 gauge

Specifications

Speaker Audio Power Amplifier (x4):

- Amplifier Type: Stereo Class-D
- Output power: 15W(RMS) per channel (@ RL=4 ohm)
- THD+N: 0.06 % (@ RL=8 ohm, f = 1 kHz)
- Minimum Load Resistance: 4 ohm
- Includes Speaker Protection circuit.

Earphone Audio Power Amplifier:

- Output power: 105mW(RMS) per channel
- THD+N: 0.05 % (@ RL=16 ohm, f = 1 kHz)
- Minimum Load Resistance: 16 ohm

Power & Dimensions:

- Power Consumed: 9A Max
- Power Source: DC 12 Volts
- Size (LxWxH): 285mm x 128mm x 43mm
- Net Weight (Unit only): 0.8 Kg