

MIC/AUX/BT 4 Zone Stereo Audio Power Amplifier **ARC-1300HBT**

The 4 Zone Stereo Audio Power Amplifier is designed with 1 input that are completely assignable to any of the 4 output zones.

FEATURES

- Inputs :Dynamic microphone, stereo audio line level or Bluetooth
- Provides line loopout expanding.
- Each audio input supports BRIDGE mode.
- Each output zone supports BRIDGE mode.
- Independent microphone level control.
- Individual speaker volume control.
- Screw terminals handle wire sizes from 24 to 12 gauge.
- Large detachable terminal block(supplied) for quick and easy installation in a structured-wiring cabinet.
- Also suitable for wall-mounting.

SPECIFICATIONS

- Microphone pre-Amplifier gain:40dB
- Bluetooth Version: Bluetooth v5.0 compliant with aptX
- Bluetooth Receive Distance: 30 Meters (open space)

Speaker Audio Power Amplifier(X4):

- Amplifier Type: Stereo Class-D
- Output power: Stereo mode 30W(rms) / ch (@ RL=4 ohm)
Bridge mode 60W(rms) / ch (@ RL=4 ohm)
- THD+N :0.1 % (@ RL=8 ohm, f = 1 kHz)
- Minimum Load Resistance : Stereo mode RL=4 ohm
Bridge mode RL=4 ohm
- Includes Speaker Protection circuit.

Power & Dimensions:

- Power Consumed: 8A Max
- Power Source: DC 24 Volts
- Size (LxWxH): 287mm x 103mm x 46mm
- Net Weight (Unit only): TBD